

Kurzweil 3000™ for Windows Version 13 USB Edition Setup Guide

Congratulations on acquiring the Kurzweil 3000 USB product! Simply plug it in, then work with, save and take Kurzweil 3000 files and settings with you on the USB device.

System Requirements

USB 2.0 port

Processor: 1.3 GHz Pentium® 4 or better

System Memory: 512 MB (1 GB for 64-bit Windows Vista and Windows 7:

NOTE: Kurzweil 3000 Professional USB scanning features are not supported on 64-bit Windows 7 operating system)

Hard Disk Space: 100 MB

Operating System: Microsoft® Windows® XP, Windows Vista®, or Windows® 7

Video Memory: 4 MB or better

Screen Resolution: 1024x768 24-bit color or better

Additional Requirements

Keyboard, mouse, SoundBlaster 16-bit compatible sound card, speakers, microphone, Internet connection. TWAIN-compatible scanner (Color and Black-and-White Professional only). Mozilla Firefox 3.5 or later, or Microsoft Internet Explorer 7 or 8.

IMPORTANT PRODUCT INFORMATION

Use and store the USB product with care. If you damage the device, lose it, or accidentally remove Kurzweil 3000 files, a replacement is available, contact Customer Service.

DO NOT MOVE KURZWEIL 3000 PROGRAM FILES AROUND ON THE USB DRIVE or REMOVE THEM FROM THE USB DRIVE.

One-Time Activation and Registration of Kurzweil 3000 USB Edition:

Activation requires an Internet connection, your serial number and product registration.

1. Insert the Kurzweil 3000 USB device into a USB 2.0 port.
2. Find and open the device folder, and double-click the Start file.
3. In the Registration message window, click OK. Next, select "Use Existing Account" or "Create New Account." If you have forgotten your user information, use Create New Account. Follow the prompts, then click Register.
4. Upon successful registration, exit Kurzweil 3000 and relaunch using the Start file in the device folder.

Starting and Exiting the USB Edition

Whenever you use the USB Edition, be sure to do the following:

- Use a USB 2.0 port.
- In the device folder, double-click the Start file.
- When you are finished, Exit Kurzweil 3000 and Stop the USB device from the Windows Taskbar before removing it. Removing the device without stopping it may damage your working files.

Setting Up Virtual Printer, Read the Web and MathPlayer

KESI Virtual Printer: To use this feature, you must first install it from the **KESI VP-Installer** (for computers running 32-bit versions of Windows) or **KESI VP64-Installer** (for computers running 64-bit versions of Windows). Both installers are in the top level of the USB device folder. NOTE: You must have Kurzweil 3000 USB open to use the Virtual Printer.

Read the Web: To use the Read the Web feature, you must choose a default Web Browser--either Internet Explorer 7 or 8, or Mozilla Firefox 3.5 or later. Firefox requires separate installation and the **kesireader** extension file (found in the top level of the USB device folder) copied onto each system. Find instructions for Web browser selection in the online Help topic, "Choosing a Default Web Browser," under "Setting Up Kurzweil 3000 Features."

MathPlayer: Reading MathML requires Internet connection, and Read the Web (see Read the Web setup) and MathPlayer installed. To install MathPlayer, go to the top level the USB device folder, then from the **MathPlayer-Installer** folder, double-click the **MathPlayerSetup** file.